



HAND HELD METAL DETECTOR

MODEL - 8, ULTRA - DLX - 1.



ULTRA -TECH SECURITY SOLUTIONS “ IS THE LEADING MANUFACTURER & SERVICE PROVIDER for Metal Detectors for Security & Pilferage Prevention application including airports, prisons, customs, banks, police department, courtrooms, public buildings, industry etc. MODEL- 8, ULTRA - DLX - 1 is our New Ultra Sensitivity detector with a target size down to 0.1gm. MODEL- 8, ULTRA - DLX – 1 Hand Held Metal Detector is light weight, rugged detector for locating hidden metal object on a person, “Gives an idea for Quantity of Metal Detection”.

FEATURES

- Operates on single 9 Volt Battery. Built-in Battery Charger.
- Battery Charging Time : 4 to 6 Hours.
- Turn Off the Detector when Charging it.
- Designed for Law enforcement, Security & Policing.
- Detects All metals, both Ferrous & non-Ferrous.
- Auto Balancing with push Button Operation.
- Highly Sensitive & Auto tune to every Application.
- Modes of Indication : Audio Alarm , & Normal mode (Blinking LED Indication).
- Working Temperature : -10° C to +55° C 0-95% HR.
- Ultra low Power consumption. // Light Weight.
- Easy to use. One Switch Operation. // Long Battery Life.
- Comfortable handle & Wrist strap for Holding. // No False Alarms.
- Continuous Operation for 100 hrs with intermittent use.
- ABS Moulded Search head & Power Coated metal Cabinet.



NOTE :

IF THE GREEN LIGHT GOES OUT COMPLETELY OR FAILS TO COME ON OR IF THE UNIT IS MAKNG UNFAMILIAR AUDIO TUNES, THE UNIT IS UNSTABLE AND SHOULD NOT BE USED UNTIL THE BATTERY IS RECHARGED OR REPLACED. IF THE UNIT IS NOT TO BE USED FOR A CERTAIN LENGTH OF TIME, IT IS ADVISABLE TO REMOVE THE BATTERY TO AVOID BATTERY LEAKAGE WHICH COULD CAUSE SERIOUS DAMAGE TO THE DETECTOR.

☒ WHEN NOT IN USE, THE DETECTOR SHOULD BE STORED IN A DRY WARM ENVIRONMENT. ☒ THIS WILL ALSO FACILITATE CLEARLY SCAN CONTRABAND GUTKA , PAN PARAG & RELATED MATERIALS IN THEIR ORIGINAL FORM OF PACKING.

SPECIFICATIONS :

Sensitivity	: Test Piece	
0.1gm Razor	20	25 mm
Knife Gold ring	Dist	60mm
4gm Coin	Dist	80mm
9.5gm	Dist	80mm
Power Consumption :	1.2 X 4 NI-CD Rechargeable Battery	
Battery Life	: Several months of Intermitted use.	

DIMENSIONS :

Length : 410mm
 Height : 23mm
 Width : 55 mm
 Weight : 450 g (Including Bty)

SOME USEFUL POINTS/TIPS TO FOLLOW BEFORE HANDLING OF THE METAL DETECTOR

A MINIMUM OF 4 FEET DISTANCE IN DIAMETER SHOULD BE MAINTAINED AROUND THE PERSON CHECKED NO MOBILE PHONES SHOULD BE IN ACTIVE MODE NEAR THE CHECKING AREA WHILE CHECKING, NO ELECTRO-MAGNETIC DISTURBANCES SHOULD BE NEAR THE CHECKING AREA FOR THE GOOD HEALTH OF THE METAL DETECTOR. THE CHECKING AREA SHOULD BE CLEAN & SANITIZED , METAL FREE FOR AROUND 4 FEET DIAMETER AROUND THE CHECKING AREA, (i.e.) Metal Doors , Metal Windows , Grill Gates , Metal Cupboards , Metal Table & Chairs Or Any Other Metal Objects. BEFORE CHECKING THE POCKETS & THE BELONGINGS IN THE PANTS & SHIRTS SHOULD BE EMPTIED. LEGS OF THE PERSON SHOULD BE RAISED ABOVE THE GROUND-LEVEL OF AROUND 1 FEET & ABOVE USING A PLASTIC STOOL,BECAUSE THERE CAN BE INVISIBLE METAL FOUND ON OR IN THE GROUND/FLOOR (Shoes Should Be Taken Extra Care Of)

PLEASE IDENTIFY ANY METAL OBJECTS EMBEDDED ON THE DRESSES WORN BY THE PERSONS. BEFORE CHECKING.

PLEASE NOTE DOWN ANY RELIGIOUS "TAAYATH / TAAVIZ "AROUND THE WAIST/ARM OF THE PERSON.

PLEASE TAKE NOTE OF ANY METAL IMPLANTS INSIDE ONE'S BODY.

PLEASE USE THE METAL DETECTOR SMOOTHLY NOT ROUGHLY,SPEEDELY,STRIKE,BANG,

FORCEFULLY WHILE CHECKING BECAUSE IT MAY GIVE SOMETIMES FALSE ALARMS SOUNDS.

WHILE CHECKING THE CURVES, UP'S & DOWN'S IN THE BODY PLEASE DO IT SLOWLY & SMOOTHLY.

PLEASE CHARGE THE METAL DETECTOR FOR 2 HOURS AFTER CHECKING AROUND 200 TO 250

PEOPLE OR WHEN THE BATTERY" LOW "IS INDICATED.

PLEASE SWITCH OFF THE METAL DETECTOR WHILE BATTERY IS IN CHARGE

PLEASE DONOT USE THE METAL DETECTOR WHILE IT'S GETTING CHARGED.

USE DRY BATTERY & RE-CHARGEABLE BATTERY OPTION SIMULTANEOUSLY.

PLEASE USE THE SAFETY NYLON WRIST STRAP/ROPE AROUND THE WRIST WHILE HANDLING THE METAL DETECTOR FROM FALLING DOWN.

PLEASE DONOT DROP THE METAL DETECTOR FORCEFULLY.HANDLE IT WITH CARE.

DO NOT ROUGHLY USE THE ON/OFF SWITCH.

PLEASE DO NOT SPEEDELY OR FORCEFULLY WAVE THE METAL DETECTOR IN THE AIR.

SUGGESTION: REQUESTED ALWAYS TO HAVE AN OPTION OF A STAND BY METAL DETECTOR

IN PLACE, IN CASE OF A SUDDEN BREAK DOWN/PROBLEM. AFTER ALL IT'S AN ELECTRONIC COMPONENT.

FOR ANY CLARIFICATION & DOUBTS PLEASE FEEL FREE TO CONTACT US.



ULTRA TECH SECURITY SOLUTIONS

No. 5, G.V.D. Layout, Opp. St., to Chinmaya Vidyalaya, Subramaniya Puram, Coimbatore - 641002.

(Near Nehru Vidyalaya, Robertson Road, R.S.Puram)

E-mail: ultratech.securitysolutions@hotmail.com // ultratechmahaveerjain@gmail.com

Website: www.ultratechsecuritysolutions.com

PH: +91-9443066502 / 9042066502, 0422-3520193

GSTIN NO : 33AAJPJ1987E1ZQ



NO.1, EXPERTS IN METAL DETECTORS & CCTV IN SOUTH INDIA